Part Number 20001/3-L-S2 Star type configuration

FM-Radio Band II 2x600W STAR COMBINER - Triple Cavity Band Pass Filter



	▶1:Tra ▶2:Off	n s mis	sian	Log	Mag	1.0	dB/ R	ef (8.00 dB	0?
dB l	2x500 Inser	W FM tion	3Cav.S	TAR T 4.900	YPE C MHz	dmB.	Ch1:	Mkr1	94.92 -0.64	10 MHz dB
Ch1 ▶						47				
- 1					<u>A</u>	A				
-2				/—		-		-	-	
- 3			-							
- 4		-						\vdash		
-5										
-6 -7			7		-					
Abs										
Center 94.900 MHz Span 2.000 MHz										
1:Mkr (MHz) dB 1> 94.90 -0.64 2: 94.75 -0.64 3: 95.05 -0.68						2:Mkr (MHz) dB				
	3: 9	5.05	-Ø.	68						

Mechanical Characteristics	
Connections	
Input	N Female
Output	DIN 7/16 or EIA 7/8"
Overall dimensions [WxDxH] [mm.]	305x460x850
Temperature range [C°]	-10 ÷ 50
Weight [kg.]	35

Electrical Characteristics						
Frequency Range [MHz]	87.5 ÷ 108					
Insertion Loss by Channels [dB]	< 0.75					
Return loss by Channels [dB]	> 26					
Input/Output Impedance [Ohm]	50					
Minimum distance between Channels [MHz]	1.2					
Insulation Between Channels [dB]	> 30					
Maximum Channel Input Power [W]	600					
Maximum Output Power [W]	1200					

